

---

# Three Phase Inverters for the 120/208V Grid for North America

SE9KUS / SE14.4KUS



INVERTERS

## The best choice for SolarEdge enabled systems

- Specifically designed to work with power optimizers
- Built-in module-level monitoring
- Quick and easy inverter commissioning directly from a smartphone using the SolarEdge SetApp
- Integrated arc fault protection and rapid shutdown for NEC 2014 and 2017, per article 690.11 and 690.12
- Internet connection through Ethernet or Wireless
- Integrated Safety Switch
- Fixed voltage inverter for longer strings
- Supplied with RS485 Surge Protection, to better withstand lightning events
- UL1741 SA certified, for CPUC Rule 21 grid compliance
- Small, lightweight, and easy to install outdoors or indoors on provided bracket

# / Three Phase Inverters for the 120/208V Grid<sup>(1)</sup> for North America

## SE9KUS / SE14.4KUS

	SE9KUS	SE14.4KUS	
<b>APPLICABLE TO INVERTERS WITH PART NUMBER</b>			
<b>SEXK-XXXXXBXX4</b>			
<b>OUTPUT</b>			
Rated AC Power Output	9000	14400	VA
Maximum AC Power Output	9000	14400	VA
Output Line Connections	3 phase, 3-wire / PE (L1-L2-L3), TN, TT 3 phase, 4-wire / PE (L1-L2-L3-N), TN, TT		
AC Output Voltage Minimum-Nominal-Maximum <sup>(2)</sup> (L-N)	105-120-132.5		Vac
AC Output Voltage Minimum-Nominal-Maximum <sup>(2)</sup> (L-L)	183-208-229		Vac
AC Frequency Min-Nom-Max <sup>(2)</sup>	59.3 - 60 - 60.5		Hz
x. Continuous Output Current (per Phase)	25	40	A
GFDI Threshold	1		A
Utility Monitoring, Islanding Protection, Country Configurable Set Points	Yes		
THD	≤ 3		%
<b>INPUT</b>			
Maximum DC Power (Module STC)	12150	19400	W
Transformer-less, Ungrounded	Yes		
Maximum Input Voltage DC to Gnd	250	300	Vdc
Maximum Input Voltage DC+ to DC-	500	600	Vdc
Nominal Input Voltage DC to Gnd	200		Vdc
Nominal Input Voltage DC+ to DC-	400		Vdc
Maximum Input Current	26.5	38	Adc
Maximum Input Short Circuit Current	45		Adc
Reverse-Polarity Protection	Yes		
Ground-Fault Isolation Detection	1MΩ Sensitivity	350kΩ Sensitivity <sup>(3)</sup>	
CEC Weighted Efficiency	96.5	97	%
Night-time Power Consumption	< 3	< 4	W
<b>ADDITIONAL FEATURES</b>			
Supported Communication Interfaces	RS485, Ethernet, Built-in GSM (Optional)		
Inverter Commissioning	With the SetApp mobile application using built-in Wi-Fi access point for local connection		
Rapid Shutdown – NEC 2014 and 2017 690.12	Automatic Rapid Shutdown upon AC Grid Disconnect		
RS485 Surge Protection	Supplied with the inverter		
Smart Energy Management	Export Limitation		
<b>STANDARD COMPLIANCE</b>			
Safety	UL1741, UL1741 SA, UL1699B, CSA C22.2, Canadian AFCI according to T.I.L. M-07		
Grid Connection Standards	IEEE1547, Rule 21, Rule 14 (HI)		
Emissions	FCC part15 class B		
<b>INSTALLATION SPECIFICATIONS</b>			
AC output conduit size / AWG range	3/4" minimum / 8-4 AWG		
DC input conduit size / AWG range	3/4" minimum / 12-6 AWG		
Number of DC inputs	3 pairs <sup>(4)</sup>		
Dimensions (H x W x D)	21 x 12.5 x 10.5 / 540 x 315 x 260		in / mm
Dimensions with Safety Switch (H x W x D)	30.5 x 12.5 x 10.5 / 775 x 315 x 260		in / mm
Weight	99.5 / 45		lb / kg
Weight with Safety Switch	106 / 48		lb / kg
Cooling	Fans (user replaceable)		
Noise	< 55		dBA
Operating Temperature Range	-40 to +140 / -40 to +60 <sup>(5)</sup>		°F / °C
Protection Rating	NEMA 3R		

(1) For 277/480V inverters refer to: <https://www.solaredge.com/sites/default/files/se-three-phase-us-inverter-277-480v-setapp-datasheet.pdf>

(2) For other regional settings please contact SolarEdge support

(3) Where permitted by local regulations

(4) Field replacement kit for 1 pair of inputs P/N: DCD-3PH-1TBK; Field replacement kit for 3 pairs of fuses and holders P/N: DCD-3PH-6FHK-S1

(5) For power de-rating information refer to: <https://www.solaredge.com/sites/default/files/se-temperature-derating-note-na.pdf>